

Product datasheet

Specifications



APC Replacement Battery Cartridge # 136 with 2 Year Warranty

APCRBC136

Overview

Lead Time Usually in Stock

Main

Product Or Component Type Replacement battery cartridge

Battery Type Lead-acid battery

Provided Equipment Installation guide

Batteries & Runtime

Battery Location Internal battery

Number Of Battery Blocks Per String 2

Number Of Battery Free Slots 0

Number Of Battery Filled Slots 0

Device Mounting Stand alone battery stack

Battery Voltage 24 V

Number Of Battery Replacement Quantity 1

Physical

Height 10.7 cm

Width 10.7 cm

Depth 14.4 cm

Net Weight 3.3 kg

Mounting Mode Not rack-mountable

Output

Battery Capacity 4.5 Ah

Environmental

Ambient Air Temperature For Operation 0...50 °C

Operating Altitude 0...10000 ft

Relative Humidity 0...95 %

Ambient Air Temperature For Storage -15...45 °C

Storage Altitude 0.00...15240.00 m

Storage Relative Humidity	0...95 %
---------------------------	----------

Packing Units

Unit Type Of Package 1	PCE
------------------------	-----

Number Of Units In Package 1	1
------------------------------	---

Package 1 Height	22.9 cm
------------------	---------

Package 1 Width	22.9 cm
-----------------	---------

Package 1 Length	22.9 cm
------------------	---------

Package 1 Weight	3.75 kg
------------------	---------

Contractual warranty

Warranty	2 years repair or replace
----------	---------------------------

Sustainability

Green Premium™ label is Schneider Electric's commitment to delivering products with best-in-class environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO₂ products.

[Learn more >](#)



Take-back Transparency RoHS/REACH

Resource performance

 Take-Back Program Available

Certifications & Standards

Reach Regulation

[REACH Declaration](#)

Eu Rohs Directive

Pro-active compliance (Product out of EU RoHS legal scope)

[EU RoHS Declaration](#)

Environmental Disclosure

[Product Environmental Profile](#)

Circularity Profile

[End of Life Information](#)